

## Split Phase Oil Burner Motors

*Designed to meet manufacturer's requirements for oil burners.*



**MTR0B2**



**MTR0B3, MTR0B4, MTR0B5**

### Features:

- Totally enclosed when mounted
- 5.6" diameter
- Manual reset thermal overload protection
- 104°F (40°C) ambient
- 1 year warranty

### COMPETITIVE CROSS REFERENCE

<b>MTR0B2</b>	AO Smith EL2002, Emerson 3083, GE 4779, Magnetek F225, Marathon 0100, Mars 30100, Sid Harvey (former) A39-31, US Motors 3083
<b>MTR0B3</b>	AO Smith EL2014, Emerson 3252, GE 4784, Magnetek 726, Marathon 0601, Mars 30601, Sid Harvey (former) A39-4, US Motors 3252
<b>MTR0B4</b>	AO Smith EL2022, Emerson 2302, GE 4785, Magnetek F335, Marathon 0004, Mars 30004, Sid Harvey (former) A39-42, US Motors 2302
<b>MTR0B5</b>	AO Smith EL2005, Emerson 3196, GE 4782, Magnetek 723, Marathon 0600, Mars 30600, Sid Harvey (former) A39-2, US Motors 3196

Available New & Remanufactured

SH Item#	SH Reman Item#	HP	RPM / Speeds	Electrical	Bearings	Insulation	Leads	Frame	Rot.	Mount	Service Factor
<b>MTR0B2</b>	<b>A39-31R*</b>	1/7	3450 1 SPD	115V 1 phase, 60 Hz 2.6 amp	Ball	Class F	24"	48M	Rev.	M-flange	1.00
<b>MTR0B3</b>	<b>A39-4R*</b>	1/6	1725 1 SPD	115V 1 phase, 60 Hz 3.1 amp	Ball	Class B	20"	48N	Rev.	N-flange	1.00
<b>MTR0B4</b>	<b>A39-44R*</b>	1/4	3450 1 SPD	115V 1 phase, 60 Hz 3.7 amp	Ball	Class B	20"	48N	Rev.	N-flange	1.00
<b>MTR0B5</b>	<b>A39-2R*</b>	1/8	1725 1 SPD	115V 1 phase, 60 Hz 2.4 amp	Ball	Class B	20"	48N	Rev.	N-flange	1.00

\* ALL SID HARVEY REMANUFACTURED PRODUCTS CARRY A 5 YEAR WARRANTY. REMANUFACTURED IN THE USA.